

KENWOOD

Listen to the Future

TK-2312/3312

Compact VHF/UHF FM Portable Radios

FleetSync®
by KENWOOD

GENERAL FEATURES

- 5 W (136-174 MHz) Model
- 5 W (400-470 MHz) Models
- Conventional Zones
- 128 Channels / 128 Zones¹
- Single Priority Scan
- Single & Multi-Zone Scan
- 8 Character Alphanumeric Aliases
- Backlit LCD
- Function / Status LCD Icons
- RSSI Indicator
- Transmit / Busy / Call Alert / Warn LED
- 4-Color LED (Blue/Red/Green/Orange)
- 7 Front Panel PF keys
- 2 Side PF Keys
- 500 mW Audio Power
- Enhanced Kenwood Audio
- Companded Audio (per CH)
- VOX Ready
- Voice Inversion Scrambler Built-in
- 16 Scrambler Codes (per CH)
- Emergency Call Features
- Lone Worker Alert
- QT / DQT
- Two-Tone Decode²
- Single / Two-Tone Encode²
- Operator Selectable Tone²
- DTMF Encode / Decode³
- FleetSync®/MDC-1200 (per Zone)

- Special Alert Tone Pattern⁴
- Call Key⁵
- Time Out Timer
- Busy Channel Lockout
- LCD Battery Status Indicator
- Low Battery Alert
- Battery Saver
- Windows® Programming & Tuning⁶
- Wireless Cloning
- Password Protection
- MIL-STD-810 C/D/E/F/G
- IP-54/55 Water & Dust Intrusion

FleetSync®

- PTT ID Digital ANI
- Selective Call & Group Call⁷
- Status Messaging⁷
- Emergency Status
- Caller ID Display⁷
- Short Text Messages⁷
- Send GPS Data (KMC-48GPS)
- PTT ID & Emergency GPS Reporting
- Status Message Block GPS Reporting

MDC-1200

- PTT ID Digital ANI
- Emergency Status
- Radio Check
- Radio Inhibit



Options

■ KNB-29N

Ni-MH Battery Pack
(1,500 mAh)



■ KSC-31

Fast Charger (3-Hour)



■ KRA-22

VHF Low Profile
Helical Antenna



■ KRA-23

UHF Low Profile
Helical Antenna



■ KRA-26

VHF Helical Antenna



■ KRA-27

UHF Whip Antenna



■ KMC-45

Speaker Microphone



■ KMC-21

Compact Speaker
Microphone



■ KMC-48GPS

GPS Speaker
Microphone



■ KEP-2

Earphone Kit
(2.5mm plug)



■ KHS-7A

Single-Muff Headset
with In-line PTT



■ KHS-8BL

2-wire Palm Mic with
Earphone (Black)



■ KHS-9BL

3-wire Lapel Mic
with Earphone (Black)



■ KHS-22

Behind-the-head
Headset with PTT



■ KHS-23

2-wire Palm Mic



■ KHS-25

D-Ring Ear Hanger
with PTT & Boom Mic



■ KHS-26

Earbud In-line
PTT Headset



■ KHS-27

D-Ring In-line
PTT Headset



■ KMB-25

Six Unit Charger
Adapter for six
KSC-31K chargers



(chargers not included)

■ KBH-10

Belt Clip



Specifications

All accessories and options may not be available in all markets.
Contact an authorized Kenwood dealer for details and complete list of all accessories and options.

Model	TK-2312	TK-3312
GENERAL		
Frequency Range		
Type 1	136-174 MHz	-
Type 2	-	400-470 MHz
Number of Channels		
Zone/Channel	Max. 128 per Radio / Max. 128 per Zone	
Channel Spacing		
Wide/Narrow	25 kHz / 12.5 kHz	
Battery Voltage	7.5V DC±20%	
Battery Life	(5-5-90 duty cycle, during hi-power, battery saver off)	
with KNB-29N (1,500mAh)	Approx. 14 hours	
Operating Temperature Range	-22°F ~ +140°F (-30°C ~ +60°C)	
Frequency Stability	±2.5ppm (-22°F ~ +140°F)	
Antenna Impedance	50 Ω	
Channel Frequency Spread		
Type 1	38 MHz	-
Type 2	-	70 MHz
Dimensions (W x H x D), Projections not Included		
Radio Only	2.13" x 4.8" x 0.83" (54 x 122 x 21.1 mm)	
with KNB-29N	2.13" x 4.8" x 1.33" (54 x 122 x 33.7 mm)	
Weight (net)		
Radio Only	6.3 oz (180 g)	
with KNB-29N	13.4 oz (380 g)	
FCC ID		
Type 1	ALH413700	-
Type 2	-	ALH413801
IC Certification		
Type 1	282D-413700	-
Type 2	-	282D-413801

Model	TK-2312	TK-3312
RECEIVER (Measurements made per TIA/EIA-603)		
Sensitivity (12dB SINAD)		
Wide		0.25 µV
Narrow		0.28 µV
Selectivity		
Wide		70 dB
Narrow		60 dB
Intermodulation Distortion		
Wide		70 dB
Narrow		60 dB
Spurious Response	70 dB	70 dB
Audio Distortion		Less than 5%
Audio Output		500 mW / 8 Ω
TRANSMITTER (Measurements made per TIA/EIA-603)		
RF Output Power		
High	5 W	5 W
Low	1 W	1 W
Spurious Response		70 dB
Type of Emission		
Wide		16K0F3E
Narrow		11K0F3E
FM Hum & Noise		
Wide		45 dB
Narrow		40 dB
Audio Distortion		Less than 5%

Kenwood reserves the right to change specifications and features without prior notice.
FleetSync® is a registered trademark of Kenwood Corporation in the United States and/or other countries.
All other trademarks are property of their respective owners.

Applicable MIL-STD & IP

Standard	MIL 810C Methods/Procedures	MIL 810D Methods/Procedures	MIL 810E Methods/Procedures	MIL 810F Methods/Procedures	MIL 810G Methods/Procedures
Low Pressure	500.1/Procedure I	500.2/Procedure I, II	500.3/Procedure I, II	500.4/Procedure I, II	500.5/Procedure I, II
High Temperature	501.1/Procedure I, II	501.2/Procedure I, II	501.3/Procedure I, II	501.4/Procedure I, II	501.5/Procedure I, II
Low Temperature	502.1/Procedure I	502.2/Procedure I, II	502.3/Procedure I, II	502.4/Procedure I, II	502.5/Procedure I, II
Temperature Shock	503.1/Procedure I	503.2/Procedure I	503.3/Procedure I	503.4/Procedure I, II	503.5/Procedure I
Solar Radiation	505.1/Procedure I	505.2/Procedure I	505.3/Procedure I	505.4/Procedure I	505.5/Procedure I
Rain	506.1/Procedure I, II	506.2/Procedure I, II	506.3/Procedure I, II	506.4/Procedure I, III	506.5/Procedure I, III
Humidity	507.1/Procedure I, II	507.2/Procedure II, III	507.3/Procedure II, III	507.4	507.5/Procedure II
Salt Fog	509.1/Procedure I	509.2/Procedure I	509.3/Procedure I	509.4	509.5
Dust	510.1/Procedure I	510.2/Procedure I	510.3/Procedure I	510.4/Procedure I, III	510.5/Procedure I
Vibration	514.2/Procedure VIII, X	514.3/Procedure I	514.4/Procedure I	514.5/Procedure I	514.6/Procedure I
Shock	516.2/Procedure I, II, V	516.3/Procedure I, IV	516.4/Procedure I, IV	516.5/Procedure I, IV	516.6/Procedure I, IV
International Protection Standard					
Dust & Water Protection	IP54/55				

*To meet IP 54/55, the 2-pin connector cover has to be connected on the radio or the locking bracket has to be attached to the KMC-45 speaker microphone.

Footnotes from front:

- Conventional Zones: 128 Channels / 128 Zones max. per radio; 128 CH max. per Zone.
- Two-Tone Decode (3 sets x 2 pairs each); Single / Two-Tone Encode (10 tones); Operator Selectable Tone (40 QT.DQT code pairs).
- DTMF Encode: PTT ID, Emergency ANI, Auto-Dial (16 numbers); DTMF Decode: Code Squelch (3-10 digit), Selective Call (9-digit with status) Group Codes A, B, C, D & Wild Card characters and Radio Stun.
- Special Alert Tone Patterns operate for 2-Tone, DTMF, FleetSync® selective call decode.
- Call Key 1, 2, & 3: operates for 2-Tone, DTMF and FleetSync® status encode.
- KPG-134D required: Windows® XP/Vista/7 compatible; English/Spanish/French screen languages.
- ID List capacity is 100 ID's; Short Text Messages are radio stored & LCD displayed; Status Message List capacity is 50.

KENWOOD

Kenwood U.S.A. Corporation
Communications Sector Headquarters
3970 Johns Creek Court, Suite 100, Suwanee, GA 30024-1265

Order Administration/Distribution
P.O. BOX 22745, 2201 East Dominguez St., Long Beach, CA 90801-5745

Kenwood Electronics Canada Inc.
Canadian Headquarters and Distribution
6070 Kestrel Road, Mississauga, Ontario, Canada L5T 1S8


www.kenwood.com



ADS#36310 Printed in USA